# NextCentury

# RR4-AU Remote Display

The NextCentury RR4-AU Remote Reader is an advanced meter reading solution which provides a high visibility remote display of one or two utility meters.

Setup and configuration is simple, with an easy-to-use mobile app available for iOS or Android devices.

The Remote Reader has an attractive consumer design, making it an ideal solution for apartment or commercial metering. The utility and unit of measure are clearly displayed, ensuring an accurate interpretation of the read.

The Remote Reader utilizes Dual Meter+<sup>™</sup> technology, making this single model compatible with virtually all modern encoded and pulse-output utility meters, including water, electric, gas, and thermal meter models.

## **IOS & ANDROID APP**

A user-friendly app for programming the display is available. It includes convenient features like meter profiles to store your preferred settings for quick programming of multiple units.

Close     Direct Connect     Save       Save     Save	3:46 🔉			<b>?</b> ₿
Et1135500 As of a few seconds ago (************************************	Close	S Direct	Connect	Save
Remote Reader RR4 Status   Alerts  View Open Alerts   Battery  Approx. 20 Years Left  Temperature  22.0 C  Show Tamper Alerts  C  C  C  C  C  C  C  C  C  C  C  C  C		E113 As of a few	5500 seconds ago	
△     Alerts     View Open Alerts >       □     Battery     Approx.20 Years Left       ⑧     Temperature     22.0 C       △     Show Tamper Alerts     Image: Compare the tamperature       Image: Compare the tamperature     Image: Compare the tamperature	Remote R			0
Battery Approx. 20 Years Left     Temperature 22.0 C     Show Tamper Alerts	Status			>
Temperature     22.0 C     Show Tamper Alerts     O	▲ Alerts		View Ope	n Alerts >
Show Tamper Alerts	🕩 Battery		Approx. 20	) Years Left
(O)	8 Tempera	ture		22.0 C
	▲ Show Ta	mper Alerts		
	Statu	s	_	

When in single meter mode, you can utilize the pulse forwarding feature to connect with an AMR system while still enjoying the benefits of having an on-site display.



### **FEATURES**

- 15+ Year Battery Life
- Dual Meter Display
- Single Meter + Output Option
- Field Programmable
- Program Current Meter Reading
- Field Replaceable Battery
- Low Battery Alert
- Tamper Detection
- IP66 Rated

### **LCD** Display



- Litres
- M3 (Kilolitres)
- BTU
- kWh
- Low Battery Alert
- Input Label
- Tamper